


IB IL 24 DO 16 ...

Inline Terminal With 16 Digital Outputs

AUTOMATIONWORX

Data Sheet
5559_en_05

© PHOENIX CONTACT - 09/2007



Description

The terminal is designed for use within an Inline station. It is used to output digital signals.

Features

- Connections for 16 digital actuators
- Connection of actuators in 2 and 3-wire technology
- Nominal current per output: 0.5 A
- Total current of the terminal: 8 A
- Short-circuit and overload protected outputs
- Diagnostic and status indicators
- **IB IL 24 DO 16, IB IL 24 DO 16-PAC and IB IL 24 DO 16-PAC/SN:**
Approved for the use in potentially explosive areas
(observe the notes on page 8)



This data sheet is only valid in association with the IL SYS INST UM E user manual or the Inline system manual for your bus system.



Please note that the numbering of the terminal points differs with regard to the different connector versions, Figure 2 on page 7.



Make sure you always use the latest documentation.
It can be downloaded at www.download.phoenixcontact.com.
A conversion table is available on the Internet at
www.download.phoenixcontact.com/general/7000_en_00.pdf.



This data sheet is valid for the products listed on the following page:

IB IL 24 DO 16 ...

Ordering Data

Products

Description	Type	Order No.	Pcs./Pkt.
Inline terminal with 16 digital outputs; complete with accessories (connector and labeling fields); transmission speed of 500 kbps	IB IL 24 DO 16-PAC	2861292	1
Inline terminal with 16 digital outputs; complete with accessories (connector with individual numbering and labeling fields); transmission speed of 500 kbps	IB IL 24 DO 16-PAC/SN	2862961	1
Inline terminal with 16 digital outputs; without accessories; transmission speed of 500 kbps	IB IL 24 DO 16	2726272	1
Inline terminal with 16 digital outputs; complete with accessories (connector and labeling fields); transmission speed of 2 Mbps	IB IL 24 DO 16-2MBD-PAC	2862013	1
Inline terminal with 16 digital outputs; complete with accessories (connector with individual numbering and labeling fields); transmission speed of 2 Mbps	IB IL 24 DO 16-2MBD-PAC/SN	2878324	1
Inline terminal with 16 digital outputs; without accessories; transmission speed of 2 Mbps	IB IL 24 DO 16-2MBD	2855318	1



Four of the listed connectors or one connector set are needed for the complete fitting of the IB IL 24 DO 16 and IB IL 24 DO 16-2MBD terminals.

Accessories

Description	Type	Order No.	Pcs./Pkt.
Connector, without color print, for digital 4-channel or 16-channel Inline terminals	IB IL SCN-12	2726340	10
Connector, with color print, for digital 4-channel or 16-channel Inline terminals	IB IL SCN-12-OCP	2727624	10
Connector set with 48 spring-cage connections (green, w/o color print)	IB IL DI/DO 16-PLSET	2860976	1
Connector set with 48 spring-cage connections (green, with color print)	IB IL DO 16-PLSET/OCP	2860992	1

Documentation

Description	Type	Order No.	Pcs./Pkt.
"Automation Terminals of the Inline Product Range" user manual	IL SYS INST UM E	2698737	1
"Configuring and Installing the INTERBUS Inline Product Range" user manual	IB IL SYS PRO UM E	2743048	1
"INTERBUS Addressing" data sheet	DB GB IBS SYS ADDRESS	9000990	1
"Inline Terminals for Use in Zone 2 Potentially Explosive Areas" application note	AH EN IL EX ZONE 2	7217	1
"Addressing of 16-Channel Modules" application note	AH IB IL 24 DI/DO 16 ADDRESS	9014124	1

Technical Data

General Data

Housing dimensions (width x height x depth)	48.8 mm x 120 mm x 71.5 mm
Weight	130 g (without connector), 152 g (with connector)
Operating mode	Process data mode with 1 word
Connection method for actuators	2 and 3-wire technology
Ambient temperatures (operation)	-25°C to +55°C
Ambient temperature (storage/transport)	-25°C to +85°C
Permissible humidity (operation/storage/transport)	10% to 95% according to DIN EN 61131-2
Permissible air pressure (operation/storage/transport)	70 kPa to 106 kPa (up to 3000 m above sea level)
Degree of protection	IP20 according to IEC 60529
Class of protection	Class 3 according to EN 61131-2, IEC 61131-2
Connection data for Inline connector	
Connection type	Spring-cage terminals
Conductor cross-section	0.2 mm ² to 1.5 mm ² (solid or stranded), 24 - 16 AWG

Interface

Local bus	Through data routing
-----------	----------------------

Transmission Speed

IB IL 24 DO 16-PAC	500 kbps
IB IL 24 DO 16-PAC/SN	500 kbps
IB IL 24 DO 16	500 kbps
IB IL 24 DO 16-2MBD-PAC	2 Mbps
IB IL 24 DO 16-2MBD-PAC/SN	2 Mbps
IB IL 24 DO 16-2MBD	2 Mbps

Supply of the Module Electronics and I/O Through Bus Coupler/Power Terminal

Connection method	Via potential routing
-------------------	-----------------------

Power Consumption

	500 kbps	2 Mbps
Communications power	7.5 V DC	7.5 V DC
Current consumption at U _L	90 mA, maximum	105 mA, maximum
Power consumption at U _L	0.675 W, maximum	0.79 W, maximum
Segment supply voltage U _S	24 V DC (nominal value)	24 V DC (nominal value)
Nominal current consumption at U _S	8 A (16 x 0.5 A), maximum	8 A (16 x 0.5 A), maximum

Digital Outputs

Number	16
Nominal output voltage U _{OUT}	24 V DC
Differential voltage for I _{nom}	≤ 1 V
Nominal current I _{nom} per channel	0.5 A
Tolerance of the nominal current	+10%
Total current	8 A
Protection	Short circuit; overload



Always 4 channels are thermally coupled, i.e., an error case in one channel can affect the other channels.

Nominal load	
Ohmic	48 Ω / 12 W
Lamp	12 W
Inductive	12 VA (1.2 H, 50 Ω)

Digital Outputs (Continued)

Signal delay upon power up of:

Nominal ohmic load	500 μ s, typical
Nominal lamp load	100 ms, typical (with switching frequencies up to 8 Hz; above this frequency the lamp load responds like an ohmic load)
Nominal inductive load	100 ms (1.2 H, 50 Ω), typical

Signal delay upon power down of:

Nominal ohmic load	1 ms, typical
Nominal lamp load	1 ms, typical
Nominal inductive load	50 ms (1.2 H, 50 Ω), typical

Switching frequency with:

Nominal ohmic load	300 Hz, maximum
--------------------	-----------------



This switching frequency is limited by the selected data rate, the number of bus devices, the bus structure, the software and the control or computer system used.

Nominal lamp load	8 Hz, maximum
-------------------	---------------



This switching frequency is limited by the selected data rate, the number of bus devices, the bus structure, the software and the control or computer system used.

Nominal inductive load	0.5 Hz (1.2 H, 50 Ω), maximum
Overload response	Auto restart
Response time with ohmic overload (12 Ω)	3 s, approximately
Restart frequency with ohmic overload	400 Hz, approximately
Restart frequency with lamp overload	400 Hz, approximately
Response with inductive overload	Output may be damaged
Response time in the event of a short circuit	3 s, approximately
Reverse voltage protection against short pulses	Protected against reverse voltages
Resistance to permanently applied reverse voltages	Protected against reverse voltages, permissible current 2 A, maximum
Validity of output data after connecting the 24 V supply voltage (power up)	5 ms, typical
Response upon power down	The output follows the supply voltage without delay.
Limitation of the voltage induced on circuit interruption	$-15 \text{ V} \leq U_{\text{demag}} \leq -45.8 \text{ V}$ (U_{demag} = demagnetization voltage)
One-time unsolicited energy	400 mJ, maximum
Protective circuit type	Integrated 45 V Zener diode in the output chip
Overcurrent circuit	0.7 A, minimum
Output current when switched off	300 μ A, maximum
Output voltage when switched off	2 V, maximum
Output current with ground connection interrupt	25 mA, maximum
Switching power with ground connection interrupt	100 mW at 1 k Ω load resistance, typical
Inrush current with lamp load	1.5 A for 20 ms, maximum

Output Characteristic Curve When Switched On (Typical)

Output Current (A)

Output Voltage Difference (V)

0	0
0.1	0.04
0.2	0.08
0.3	0.12
0.4	0.16
0.5	0.20

Power Dissipation

500 kbps

2 Mbps

Formulas to Calculate the Power Dissipation of the Electronics

$$P_{EL} = 0.19 \text{ W} + \sum_{i=1}^n (0.10 \text{ W} + I_{Li}^2 \times 0.4 \Omega)$$

$$P_{EL} = 0.40 \text{ W} + \sum_{i=1}^n (0.10 \text{ W} + I_{Li}^2 \times 0.4 \Omega)$$

Where

P_{EL} Total power dissipation in the terminal

i Continuous index

n Number of set outputs ($n = 1$ to 16)

I_{Li} Load current of the output i

Power Dissipation of the Housing P_{HOU} (500 kbps and 2 Mbps)

2.7 W, maximum (within the permissible operating temperature)

Limitation of Simultaneity, Derating

(500 kbps and 2 Mbps)

Ambient Temperature T_A	Maximum Load Current at 100% Simultaneity	Maximum Load Current at 75% Simultaneity
-25°C ≤ T_A < +40°C	0.50	0.50
+40°C ≤ T_A < +45°C	0.45	0.50
+45°C ≤ T_A < +50°C	0.40	0.50
+50°C ≤ T_A < +55°C	0.35	0.50

Safety Equipment

Overload/short circuit in segment circuit

Electronic; with four 4-channel drivers

Surge voltage

Protective elements of the power terminal

Polarity reversal of the supply voltage

Protection up to 33 V DC

Reverse voltage

Protective elements of the power terminal

The supply voltage must be protected. The power supply unit should be able to supply four times (400%) the nominal current of the fuse.

Integrated protection against reverse voltages

Electrical Isolation/Isolation of the Voltage Areas



To provide electrical isolation between the logic level and the I/O area it is necessary to supply the station bus coupler and the digital output terminal described here via the bus coupler or a power terminal from separate power supply units. Interconnection of the power supply units in the 24 V area is not permitted. (See also user manual.)

Common Potentials

The 24 V main voltage, 24 V segment voltage, and GND have the same potential. FE is a separate potential area.

Separate Potentials in the System Consisting of Bus Coupler/Power Terminal and I/O Terminal

Test Distance

5 V supply incoming remote bus/7.5 V supply (bus logic)

5 V supply outgoing remote bus/7.5 V supply (bus logic)

7.5 V supply (bus logic)/24 V supply (I/O)

24 V supply (I/O) / functional earth ground

Test Voltage

500 V AC, 50 Hz, 1 min

Error Messages to the Higher-Level Control or Computer System

Short circuit/overload of an output

Yes



An error message is generated when an output is short circuited and switched on. In addition, the diagnostic LED (D) flashes on the terminal at 2 Hz (medium) under these conditions.

Falling below or exceeding the operating voltage

No

Approvals

For the latest approvals, please visit www.download.phoenixcontact.com or www.eshop.phoenixcontact.com.

Local Diagnostic and Status Indicators and Terminal Point Assignment

Local Diagnostic and Status Indicators




Figure 1 Diagnostic and status indicators

Terminal Point Assignment for Each Connector




Figure 2 Terminal point numbering:
individual connectors (A) and connector sets (B)

Des.	Color	Meaning
D	Green	Diagnostics
1, 2, 3, 4	Yellow	Status indicators of the outputs

Function Identification


Pink

2 Mbps: white stripe in the vicinity of the D LED

- A – Using the IB IL 24 DO 16-PAC/SN or IB IL 24 DO 16-2MBD-PAC/SN with the supplied connectors
- Using individual connectors (IB IL SCN-12 or IB IL SCN-12-OCP)
- B – Using the IB IL 24 DO 16-PAC or IB IL 24 DO 16-2MBD-PAC with the original connector set
- Using the IB IL DO 16-PLSET/OCP or IB IL DI/DO 16-PLSET connector sets

Terminal Point	Assignment
x.1	Signal output (OUT)
x.2	Ground contact (GND) for 2 and 3-wire termination
x.3	FE connection for 3-wire termination
x.4	Signal output (OUT)
x.5	Ground contact (GND) for 2 and 3-wire termination
x.6	FE connection for 3-wire termination

Internal Circuit Diagram



5559B003

Figure 4 Internal wiring of the terminal points

Key:

-  OPC Protocol chip (bus logic including voltage conditioning)
-  LED
-  Optocoupler
-  Transistor
-  Digital output
-  Electrically isolated area



Other symbols used are explained in the IL SYS INST UM E user manual or in the Inline system manual for your bus system.

Connection Example



When connecting the actuators observe the assignment of the terminal points to the process data (see page 11).




Figure 5 Typical actuator connection

A 3-wire termination
B 2-wire termination

The numbers above the module illustration identify the connector slots.

Programming Data/Configuration Data

Local Bus (INTERBUS)

ID code	BD _{hex} (189 _{dec})
Length code	01 _{hex}
Process data channel	16 bits
Input address area	0 words
Output address area	1 word
Parameter channel (PCP)	0 words
Register length (bus)	1 word

Other Bus Systems



For the programming data/configuration data of other bus systems, please refer to the corresponding electronic device data sheet (e.g., GSD, EDS).

Process Data



For the assignment of the illustrated (byte.bit) view to your **INTERBUS** control or computer system, please refer to the DB GB IBS SYS ADDRESS data sheet.

For the assignment of the illustrated (byte.bit) view to control systems of **other bus systems**, please refer to the AH IB IL 24 DI/DO 16 ADDRESS document.

Assignment of the Terminal Points to the OUT Process Data



The following table applies to the IB IL 24 DO 16-PAC and IB IL 24 DO 16-2MBD-PAC terminals with the original connector set and when using the connector sets IB IL DI/DO 16-PLSET or IB IL DO 16-PLSET/OCP (see also Figure 2 on page 7, detail B).

(Byte.bit) view	Byte	Byte 0								Byte 1							
		7	6	5	4	3	2	1	0	7	6	5	4	3	2	1	0
Assignment	Slot	4				3				2				1			
	Terminal point (signal)	8.4	7.4	8.1	7.1	6.4	5.4	6.1	5.1	4.4	3.4	4.1	3.1	2.4	1.4	2.1	1.1
	Terminal point (GND)	8.5	7.5	8.2	7.2	6.5	5.5	6.2	5.2	4.5	3.5	4.2	3.2	2.5	1.5	2.2	1.2
	Terminal point (FE)	8.6	7.6	8.3	7.3	6.6	5.6	6.3	5.3	4.6	3.6	4.3	3.3	2.6	1.6	2.3	1.3
Status indicators	Slot	4				3				2				1			
	LED	4	3	2	1	4	3	2	1	4	3	2	1	4	3	2	1



The following table applies to the IB IL 24 DO 16-PAC/SN and IB IL 24 DO 16-2MBD-PAC/SN terminals with the original connector set and when using the IB IL SCN-12 or IB IL SCN-12-OPC connectors (see also Figure 2 on page 7, detail A).

(Byte.bit) view	Byte	Byte 0								Byte 1							
		7	6	5	4	3	2	1	0	7	6	5	4	3	2	1	0
Assignment	Slot	4				3				2				1			
	Terminal point (signal)	2.4	1.4	2.1	1.1	2.4	1.4	2.1	1.1	2.4	1.4	2.1	1.1	2.4	1.4	2.1	1.1
	Terminal point (GND)	2.5	1.5	2.2	1.2	2.5	1.5	2.2	1.2	2.5	1.5	2.2	1.2	2.5	1.5	2.2	1.2
	Terminal point (FE)	2.6	1.6	2.3	1.3	2.6	1.6	2.3	1.3	2.6	1.6	2.3	1.3	2.6	1.6	2.3	1.3
Status indicators	Slot	4				3				2				1			
	LED	4	3	2	1	4	3	2	1	4	3	2	1	4	3	2	1

© PHOENIX CONTACT 09/2007