

WS72142


300nA Nano-Power Rail-to-Rail Input Output Operational Amplifiers

[Http://www.willsemi.com](http://www.willsemi.com)


Descriptions

The WS72142 is a dual low-voltage operational amplifier with rail-to-rail input/output swing. Ultra low power makes this amplifier ideal for battery-powered and portable applications. The WS72142 has a gain-bandwidth product of 13kHz (TYP) and is unity gain stable. These specifications make this operational amplifier appropriate for low frequency applications, such as battery current monitoring and sensor conditioning.


WS72142 is available with MSL 3 Level in SOP-8L package and MSOP-8L package. Standard products are Pb-Free and halogen-Free.



SOP-8L MSOP-8L



SOP-8L/MSOP-8L
Pin configuration (Top view)



SOP-8L MSOP-8L

Marking

2142	= Device code
GS	= Special code
GM	= Special code
Y	= Year code
W	= Week code

Order Information

Device	Package	Shipping
WS72142S-8/TR	SOP-8L	4000/Reel & Tape
WS72142M-8/TR	MSOP-8L	4000/Reel & Tape

Features

- Wide Supply Voltage : 1.6~5.5V
- Quiescent Current per Amplifier : 300nA Typical
- GBWP : 13kHz
- Rail-to-Rail Input/Output Swing
- Unity Gain Stable
- -40°C to 125°C Operation Temperature Range
- Available in Green SOP-8L and MSOP-8L Packages

Pin Descriptions

Pin Number	Symbol	Descriptions
1	OUTA	Output
2	-INA	Inverting input
3	+INA	Non-inverting input
4	V-	Negative supply
5	+INB	Non-inverting input
6	-INB	Inverting input
7	OUTB	Output
8	V+	Positive supply

Absolute Maximum Ratings⁽¹⁾

Parameter	Symbol	Value	Unit
Supply Voltage, ($[V^+] - [V^-]$)	$V_S^{(2)}$	6	V
Input Common Mode Voltage Range	V_{ICR}	$(V^-)-0.3$ to $(V^+)+0.3$	V
Output Short-Circuit Duration	$t_{SO}^{(3)}$	Unlimited	/
Operating Fee-Air Temperature Range	T_A	-40 to 125	°C
Storage Temperature Range	T_{STG}	-65 to 150	°C
Junction Temperature Range	T_J	150	°C
Lead Temperature Range	T_L	260	°C

Note:

1. Stresses beyond those listed under Absolute Maximum Ratings may cause permanent damage to the device. These are only stress ratings, and functional operation of the device at these or any other conditions beyond those indicated under recommended operating conditions are not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.
2. All voltage values, except differential voltage are with respect to network terminal.
3. A heat sink may be required to keep the junction temperature below the absolute maximum, depends on the power supply voltage and how many amplifiers are shorted. Thermal resistance varies the amount of PC board metal connected to the package. The specified values are for short traces connected to leads.

ESD, Electrostatic Discharge Protection

Symbol	Parameter	Condition	Minimum level	Unit
HBM	Human Body Model ESD	MIL-STD-883H Method 3015.8 JEDEC-EIA/JESD22-A114A	±8000	V
CDM	Charged Device Model ESD	JEDEC-EIA/JESD22-C101E	±2000	V
MM	Machine Model ESD	JEDEC-EIA/JESD22-A115	±400	V

Electronics Characteristics







The *denotes the specifications which apply over the full operating temperature range, otherwise specifications are at $T_A = 27^\circ\text{C}$. $V_S = 5\text{V}$, $V_{CM} = V_{OUT} = V_S/2$, $R_{load} = 100\text{k}\Omega$, $C_{load} = 60\text{pF}$.







Symbol	Parameter	Conditions	Min.	Typ.	Max.	Unit
V_{OS}	Input Offset Voltage	$V_{CM}=V_S/2$ and $V_{CM}=\text{GND}$	*	-3.5	± 0.1	3.5
α_{VOS}	Input Offset Voltage Drift			1.6		$\mu\text{V}/^\circ\text{C}$
I_{IB}	Input Bias Current			<10		pA
I_{OS}	Input Offset Current			<10		pA
V_n	Input Voltage Noise	f=0.1Hz to 10Hz		8		$\mu\text{V}_{\text{P-P}}$
e_n	Input Voltage Noise Density	f=1kHz		80		nV/ $\sqrt{\text{Hz}}$
R_{IN}	Input Resistance			>1		T Ω
CMRR	Common Mode Rejection Ratio	$V_{CM}=0.1\text{V}$ to 4.9V	*	55	75	dB
V_{CM}	Common Mode Input Voltage Range		*	(V ⁻)-0.3	(V ⁺)+0.3	V
PSRR	Power Supply Rejection Ratio		*	65	91	dB
A_{VOL}	Open Loop Large Signal Gain	$V_{OUT}=2.5\text{V}, R_{load}=100\text{k}\Omega$		118		dB
		$V_{OUT}=0.1\text{V}$ to 4.9V, $R_{load}=100\text{k}\Omega$	*	85	118	dB
V_{OL}, V_{OH}	Output Swing from Supply Rail	$R_{load}=100\text{k}\Omega$		5		mV
R_{OUT}	Closed-Loop Output Impedance	$G=1, f=1\text{kHz}, I_{OUT}=0$		4.3		Ω
I_{SC}	Output Short-Circuit Current	Sink or Source Current	12	15		mA
V_{DD}	Supply Voltage		1.6		5.5	V
I_Q	Quiescent Current per Amplifier		*	300	450	nA
PM	Phase Margin	$R_{load}=100\text{k}\Omega, C_{load}=60\text{pF}$		80		degrees
GM	Gain Margin	$R_{load}=100\text{k}\Omega, C_{load}=60\text{pF}$		18		dB
GBWP	Gain-Bandwidth Product	f=1kHz		13		kHz
t_s	Settling Time	1.5 to 3.5V, Unity Gain	0.1%		0.4	ms
		2.45 to 2.55V, Unity Gain	0.1%		0.04	
SR	Slew Rate	$A_v=1, V_{OUT}=1.5\text{V}$ to 3.5V, $R_{load}=100\text{k}\Omega, C_{load}=60\text{pF}$		7		$\text{mV}/\mu\text{s}$
FPBW	Full Power Bandwidth ^{Note1}	$2V_{\text{P-P}}$		300		Hz

Note:







1. Full power bandwidth is calculated from the slew rate $\text{FPBW} = \text{SR}/(\pi \cdot V_{\text{P-P}})$.



Typical Characteristics
 $T_A=25^\circ\text{C}$, $V_s=5\text{V}$, $V_{CM}=V_s/2$, unless otherwise noted

Small-Signal Step Response, 100mV Step

Large-Signal Step Response, 2V Step

Open-Loop Gain and Phase

Phase Margin vs. C_{load} (Stable for Any C_{load})

Input Voltage Noise Spectral Density

CMRR vs. Frequency


Typical Characteristics (continued)
 $T_A=25^\circ\text{C}$, $V_s=5\text{V}$, $V_{CM}=V_s/2$, unless otherwise noted



Typical Characteristics (continued)
 $T_A=25^\circ\text{C}$, $V_s=5\text{V}$, $V_{CM}=V_s/2$, unless otherwise noted

Quiescent Supply Current vs. Temperature

Quiescent Supply Current vs. Supply Voltage

Short-Circuit Current vs. Supply Voltage

Closed-Loop Output Impedance vs. Frequency

PSRR vs. Temperature

CMRR vs. Temperature


Typical Characteristics (continued) $T_A=25^\circ\text{C}$, $V_S=5\text{V}$, $V_{CM}=V_S/2$, unless otherwise noted**Input Offset Voltage vs. Common Mode Input Voltage****0.1Hz to 10Hz Time Domain Output Voltage Noise**

Application Circuit


(1) WS72142 in Low Side Battery Current Sensor



Application Circuit for Low Side Battery Current Sensor



$$V_{OUT} = I_{CC} \times R_3 \times \left(\frac{R_1}{R_2} + 1 \right)$$

(2) WS72142 in High Side Battery Current Sensor






Application Circuit for High Side Battery Current Sensor



$$I_S = \frac{+V_S - V_{OUT}}{R_1 \times R_3 \div R_2}$$

PACKAGE OUTLINE DIMENSIONS
SOP-8L

TOP VIEW
SIDE VIEW

SIDE VIEW




Symbol	Dimensions In Millimeters (mm)		
	Min.	Typ.	Max.
A	1.35	1.55	1.75
A1	0.05	0.15	0.25
A2	1.25	1.40	1.65
b	0.33	-	0.51
c	0.15	-	0.26
D	4.70	4.90	5.10
E	3.70	3.90	4.10
E1	5.80	6.00	6.20
e	1.27BSC		
L	0.40	-	1.27
θ	0°	-	8°

TAPE AND REEL INFORMATION
SOP-8L
Reel Dimensions

Tape Dimensions

Quadrant Assignments For PIN1 Orientation In Tape


RD	Reel Dimension	<input type="checkbox"/> 7inch <input checked="" type="checkbox"/> 13inch
W	Overall width of the carrier tape	<input type="checkbox"/> 8mm <input checked="" type="checkbox"/> 12mm
P1	Pitch between successive cavity centers	<input type="checkbox"/> 2mm <input type="checkbox"/> 4mm <input checked="" type="checkbox"/> 8mm
Pin1	Pin1 Quadrant	<input checked="" type="checkbox"/> Q1 <input type="checkbox"/> Q2 <input type="checkbox"/> Q3 <input type="checkbox"/> Q4

PACKAGE OUTLINE DIMENSIONS
MSOP-8L

TOP VIEW
SIDE VIEW

SIDE VIEW

Symbol	Dimensions In Millimeters (mm)		
	Min.	Typ.	Max.
A	-	-	1.10
A1	0.02	-	0.15
A2	0.75	0.80	0.95
b	0.25	-	0.38
c	0.09	-	0.23
D	2.90	3.00	3.10
E	4.75	4.90	5.05
E1	2.90	3.00	3.10
e	0.65 BSC		
L	0.40	-	0.80
θ	0°	-	6°

TAPE AND REEL INFORMATION
MSOP-8L
Reel Dimensions

Tape Dimensions

Quadrant Assignments For PIN1 Orientation In Tape


RD	Reel Dimension	<input type="checkbox"/> 7inch <input checked="" type="checkbox"/> 13inch
W	Overall width of the carrier tape	<input type="checkbox"/> 8mm <input checked="" type="checkbox"/> 12mm
P1	Pitch between successive cavity centers	<input type="checkbox"/> 2mm <input type="checkbox"/> 4mm <input checked="" type="checkbox"/> 8mm
Pin1	Pin1 Quadrant	<input checked="" type="checkbox"/> Q1 <input type="checkbox"/> Q2 <input type="checkbox"/> Q3 <input type="checkbox"/> Q4