

# 2 in 1 SMD Rework Station



## Features

- 2 in 1 SMD Soldering Rework Station
- MCU and PID algorithm controlled temperature
- Double-window LCD display
- High flow diaphragm pump for variety of nozzles
- Dormancy, Automatic shut-off and sleep mode
- Memory stores up to three air & temperature presets
- Intelligent cooling system and deferred power-off function
- Built-in patent auger-type heating core
- Malfunction alert function
- Includes Rework Station, 4 Nozzles and power cord
- Soldering & Rework station, Nozzle, Bracket and Power Cords



## Technical Specifications

Input Voltage	220V AC 50Hz	
Total Power	900W Max.	Air heating: 800W Max, Pump: 40W
		Soldering Iron: 50W
Temperature Range	Hot Air Rework Station	100°C to 500°C
	Soldering Station	200°C to 480°C
Temperature Unit	°C / °F	Convertible
Temperature Controlling Stability	Static	±2°C
Temperature Controlling Accuracy	Static	±10°C
Calibration Range	Celsius	50°C to -50°C
	Fahrenheit	-58°F to 122°F
Setting Storage (3 groups)	Hot Air Rework Station	200°C, 40% flow; 300°C, 60% flow; 400°C, 80% flow
	Soldering Station	200°C; 300°C; 400°C
Range of Air Volume	Hot Air Rework Station	020 - 100 level
Dimensions (L × W × H)	245mm × 187mm × 135mm	
Weight	4.4kg	

## Part Number Table

Description	Part Number
2 in 1 SMD Soldering Rework Station, 900W, 220V AC, UK/EU Plug	21-10130 UK+EU

**Important Notice :** This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell Limited 2016.

www.element14.com  
 www.farnell.com  
 www.newark.com  
 www.cpc.co.uk

