


Ultra HiQ-CBR Squared Series, 0505 Case Size

High Power (1.0 – 10 pF)

Sample Kit Contents

KEMET Part Number	Case Size	Capacitance	Capacitance Tolerance	Rated Voltage	Dielectric	Quantity
	EIA/Metric	pF	%	VDC		
CBR05C109BAGAC	0505/1414	1.0	±0.10	250	C0G	50
CBR05C129BAGAC	0505/1414	1.2	±0.10	250	C0G	50
CBR05C159BAGAC	0505/1414	1.5	±0.10	250	C0G	50
CBR05C189BAGAC	0505/1414	1.8	±0.10	250	C0G	50
CBR05C209BAGAC	0505/1414	2.0	±0.10	250	C0G	50
CBR05C229BAGAC	0505/1414	2.2	±0.10	250	C0G	50
CBR05C249BAGAC	0505/1414	2.4	±0.10	250	C0G	50
CBR05C279BAGAC	0505/1414	2.7	±0.10	250	C0G	50
CBR05C309BAGAC	0505/1414	3.0	±0.10	250	C0G	50
CBR05C339BAGAC	0505/1414	3.3	±0.10	250	C0G	50
CBR05C399BAGAC	0505/1414	3.9	±0.10	250	C0G	50
CBR05C479BAGAC	0505/1414	4.7	±0.10	250	C0G	50
CBR05C519CAGAC	0505/1414	5.1	±0.25	250	C0G	50
CBR05C569CAGAC	0505/1414	5.6	±0.25	250	C0G	50
CBR05C689CAGAC	0505/1414	6.8	±0.25	250	C0G	50
CBR05C829CAGAC	0505/1414	8.2	±0.25	250	C0G	50
CBR05C100JAGAC	0505/1414	10	±5	250	C0G	50

Dimensions – Millimeters (Inches)



Case Size (in.)	Case Size (mm)	L Length	W Width	T Thickness	B Bandwidth	Mounting Technique
0505	1414	1.40+0.38/-0.25 (0.055+0.015/-0.01)	1.40±0.38 (0.055±0.015)	1.15±0.15 (0.045±0.006)	0.25+0.25-0.13 (0.010+0.010-0.005)	Solder Reflow Only

KEMET Electronics Corporation Sales Offices

For a complete list of our global sales offices, please visit www.kemet.com/sales.

Disclaimer

YAGEO Corporation and its affiliates do not recommend the use of commercial or automotive grade products for high reliability applications or manned space flight.

All product specifications, statements, information and data (collectively, the "Information") in this datasheet are subject to change. The customer is responsible for checking and verifying the extent to which the Information contained in this publication is applicable to an order at the time the order is placed. All Information given herein is believed to be accurate and reliable, but it is presented without guarantee, warranty, or responsibility of any kind, expressed or implied.

Statements of suitability for certain applications are based on KEMET Electronics Corporation's ("KEMET") knowledge of typical operating conditions for such applications, but are not intended to constitute – and KEMET specifically disclaims – any warranty concerning suitability for a specific customer application or use. The Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by KEMET with reference to the use of KEMET's products is given gratis, and KEMET assumes no obligation or liability for the advice given or results obtained.

Although KEMET designs and manufactures its products to the most stringent quality and safety standards, given the current state of the art, isolated component failures may still occur. Accordingly, customer applications which require a high degree of reliability or safety should employ suitable designs or other safeguards (such as installation of protective circuitry or redundancies) in order to ensure that the failure of an electrical component does not result in a risk of personal injury or property damage.

Although all product-related warnings, cautions and notes must be observed, the customer should not assume that all safety measures are indicated or that other measures may not be required.