



Item description

The WAGO USB Communication Cable connects a PC (notebook) to both the service interface of the 857 Series Signal Conditioners and the configuration interface of the WAGO I/O Fieldbus Couplers/Controllers.

Notice!

Using the WAGO 759-923 USB Communication Cable
in combination with select programmable fieldbus controllers
requires the specific firmware versions listed below:

- 750-841: Firmware Version 12 (or higher)
- 750-872/0020-0000: Firmware Version 2 (or higher)

Data
Technical data

Connection type	4-pole male connector - USB A-type plug
Pole number	4
Cable length	2.5 m

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG
Hansastr. 27
32423 Minden
Phone: +49571 887-0 | Fax: +49571 887-169
Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
We are always happy to take your call at +49 (571) 887-44222.



Supported operating systems

Windows XP (SP3 or higher)
 Windows 7
 Windows 10
 Windows 11

Physical data

Width	15 mm / 0.591 inches
Height	50 mm / 1.97 inches
Depth	19 mm / 0.748 inches

Mechanical Data

Sheathed cable color	black
Weight	64.8 g
Color	black

Environmental requirements

Ambient temperature (operation)	-25 ... +70 °C
Protection type	IP20
EMC immunity to interference	per EN 61000-4-3, EN 61000-4-6
EMC emission of interference	per EN 55022
Fire load	0.132 MJ

Commercial data

Product Group	15 (I/O System)
eCl@ss 10.0	27-24-22-20
eCl@ss 9.0	27-24-22-20
ETIM 8.0	EC000237
ETIM 7.0	EC000237
PU (SPU)	1 pcs
Packaging type	bag
Country of origin	DE
GTIN	4045454571641
Customs tariff number	85444290900

Environmental Product Compliance

RoHS Compliance Status	Compliant, With Exemption
RoHS Exemption	7(a)

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG
 Hansastr. 27
 32423 Minden
 Phone: +49571 887-0 | Fax: +49571 887-169
 Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
 We are always happy to take your call at +49 (571) 887-44222.

7(c)-I

Approvals / Certificates

General approvals

Logo	Approval	Additional Approval Text	Certificate name
	EAC Brjansker Zertifizierungsstelle	TP TC 020/2011	EAC RU C-DE.AM02.B.00087/19

Declarations of conformity and manufacturer's declarations

Logo	Approval	Additional Approval Text	Certificate name
	EU-Declaration of Conformity WAGO GmbH & Co. KG	-	-

Downloads

Documentation

Manual

System Manual WAGO I/O System 750/753 Decentralized Automation Technology	V 3.3.3 2023 Aug 29	pdf 8.7 MB	Download
--	------------------------	---------------	----------

Bid Text

750-923 docx - Datei	2019 Jun 26	docx 14.9 kB	Download
-------------------------	-------------	-----------------	----------

750-923 X81 - Datei	2019 Feb 19	xml 4.0 kB	Download
------------------------	-------------	---------------	----------

ausschreiben.de 750-923		URL	Download
-------------------------	--	-----	----------

Tutorial

Set IP address with Ethernet Settings	3.0 2017 Dec 18	mp4 88.3 MB	Download
---------------------------------------	--------------------	----------------	----------

Subject to changes. Please also observe the further product documentation!



In this video we are demonstrating how you can set a IP address with Ethernet Settings. Content: 00:27 – Chapter #1 Download and install software; 00:56 – Chapter #2 Open Ethernet Settings; 01:10 – Chapter #3 Establish serial Connection; 01:34 – Chapter #4 Set IP address; 02:10 – Chapter #5 Check IP address

System Description

750/753 Series I/O-System – General Product Information	pdf 976.2 kB	Download
---	-----------------	----------

CAD/CAE-Data

CAE data

EPLAN Data Portal 750-923	URL	Download
WSCAD Universe 750-923	URL	Download

Device Files

Device Driver

WAGO USB Service Kabel Treiber / Serie 750 und 857	6.5.3.0 2014 Sep 10	zip 4.8 MB	Download
--	------------------------	---------------	----------

Environmental Product Compliance

Compliance Search

Environmental Product Compliance 750-923 Configuration cable; USB connector; Length: 2.5 m	URL	Download
---	-----	----------

Installation Notes

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG
Hansastr. 27
32423 Minden
Phone: +49571 887-0 | Fax: +49571 887-169
Email: info.de@wago.com | Web: www.wago.com

Do you have any questions about our products?
We are always happy to take your call at +49 (571) 887-44222.