

WQC品牌CBB21 电容选型表

容量 (pF)	脚距 (mm)	电压 (V)	尺寸W:H:T (mm)	料号
CBB21 0.56UF	P=15MM	400V	17*12.3*5.5	C322G564J15L230A60
CBB21 0.56UF	P=15MM	250V	17*12*5.5	C322E564J15L230A60
CBB21 0.47UF	P=15MM	630V	17*15*8.3	C322J474J15L230A60
CBB21 0.47UF	P=15MM	630V	17*13.5*6.5	C322S474J15L230A60
CBB21 0.47UF	P=15MM	400V	17*13.5*6.5	C322G474J15L230A60
CBB21 0.47UF	P=15MM	250V	17*11.5*5.8	C322E474J15L230A60
CBB21 0.33UF	P=15MM	630V	17*13.5*7.6	C322J334J15L230A60
CBB21 0.33UF	P=15MM	400V	17*12*6.5	C322G334J15L230A60
CBB21 0.33UF	P=15MM	250V	17*10.3*5.2	C322E334J15L230A60
CBB21 0.22UF	P=15MM	630V	17*13.5*7.5	C322J224J15L230A60
CBB21 0.22UF	P=15MM	450V	17*12*6	C322S224J15L230A60
CBB21 0.22UF	P=15MM	400V	17*12*6	C322G224J15L230A60
CBB21 0.22UF	P=15MM	250V	17*10.2*4.3	C322E224J15L230A60
CBB21 0.15UF	P=15MM	630V	17*12.4*7	C322J154J15L230A60
CBB21 0.15UF	P=15MM	450V	17*10.3*5.2	C322S154J15L230A60
CBB21 0.15UF	P=15MM	250V	17*10.3*5.2	C322G154J15L230A60
CBB21 0.15UF	P=15MM	250V	17*10.3*5	C322E154J15L230A60
CBB21 0.1UF	P=15MM	630V	17*11.5*5.6	C322J104J15L230A60
CBB21 0.1UF	P=15MM	450V	17*10.5*5	C322S104J15L230A60
CBB21 0.1UF	P=15MM	250V	17*10.5*5	C322G104J15L230A60
CBB21 0.1UF	P=15MM	250V	17*10.4*5	C322E104J15L230A60