

# MSKSEMI 美森科

SEMICONDUCTOR



ESD



TVS



TSS



MOV



GDT



PLED

## **MS3134KDFN**

---

### **Product specification**

**Features**




- 20V, 750mA, RDS(ON) = 200mΩ@VGS = 4.5V
- Fast switching
- Green Device Available
- 2KV HBM ESD Capability

**Application**

- Notebook
- Smartphone
- Battery Protection
- Hand-held Instruments

BVDSS	RDS(ON)	ID
20V	200mΩ	750mA

**Reference News**

PACKAGE OUTLINE	Pin Configuration	Marking
 <p>DFN1006-3</p>		

**Absolute Maximum Ratings Tc=25°C unless otherwise noted**

Symbol	Parameter	Rating	Units
V <sub>DS</sub>	Drain-Source Voltage	20	V
V <sub>GS</sub>	Gate-Source Voltage	±10	V
I <sub>D</sub>	Drain Current - Continuous (T <sub>A</sub> =25°C)	750	mA
	Drain Current - Continuous (T <sub>A</sub> =70°C)	400	mA
I <sub>DM</sub>	Drain Current - Pulsed <sup>1</sup>	2000	mA
P <sub>D</sub>	Power Dissipation (T <sub>A</sub> =25°C)	155	mW
	Power Dissipation - Derate above 25°C	1.25	mW/°C
T <sub>STG</sub>	Storage Temperature Range	-55 to 150	°C
T <sub>J</sub>	Operating Junction Temperature Range	-55 to 125	°C

**Thermal Characteristics**

Symbol	Parameter	Typ.	Max.	Unit
R <sub>θJA</sub>	Thermal Resistance Junction to ambient	---	800	°C/W

## Electrical Characteristics (T<sub>J</sub>=25 °C, unless otherwise noted)

### Off Characteristics

Symbol	Parameter	Conditions	Min.	Typ.	Max.	Unit
BV <sub>DSS</sub>	Drain-Source Breakdown Voltage	V <sub>GS</sub> =0V , I <sub>D</sub> =250uA	20	---	---	V
ΔBV <sub>DSS</sub> /ΔT <sub>J</sub>	BV <sub>DSS</sub> Temperature Coefficient	Reference to 25°C , I <sub>D</sub> =1mA	---	-0.01	---	V/°C
I <sub>DSS</sub>	Drain-Source Leakage Current	V <sub>DS</sub> =20V , V <sub>GS</sub> =0V , T <sub>J</sub> =25°C	---	---	1	uA
		V <sub>DS</sub> =16V , V <sub>GS</sub> =0V , T <sub>J</sub> =125°C	---	---	10	uA
I <sub>GSS</sub>	Gate-Source Leakage Current	V <sub>GS</sub> = ±10V , V <sub>DS</sub> =0V	---	---	±10	uA

### On Characteristics

R <sub>DS(on)</sub>	Static Drain-Source On-Resistance	V <sub>GS</sub> =4.5V , I <sub>D</sub> =0.5A	---	200	350	mΩ
		V <sub>GS</sub> =2.5V , I <sub>D</sub> =0.4A	---	235	450	
		V <sub>GS</sub> =1.8V , I <sub>D</sub> =0.2A	---	295	700	
V <sub>GS(th)</sub>	Gate Threshold Voltage	V <sub>GS</sub> =V <sub>DS</sub> , I <sub>D</sub> =250uA	0.3	0.5	0.8	V
ΔV <sub>GS(th)</sub>	V <sub>GS(th)</sub> Temperature Coefficient		---	3	---	mV/°C

### Dynamic and switching Characteristics


Q <sub>g</sub>	Total Gate Charge <sup>2, 3</sup>	V <sub>DS</sub> =10V , V <sub>GS</sub> =4.5V , I <sub>D</sub> =0.5A	---	1	---	nC
Q <sub>gs</sub>	Gate-Source Charge <sup>2, 3</sup>		---	0.26	---	
Q <sub>gd</sub>	Gate-Drain Charge <sup>2, 3</sup>		---	0.2	---	
T <sub>d(on)</sub>	Turn-On Delay Time <sup>2, 3</sup>	V <sub>DD</sub> =10V , V <sub>GS</sub> =4.5V , R <sub>G</sub> =10Ω I <sub>D</sub> =0.5A	---	5	---	ns
T <sub>r</sub>	Rise Time <sup>2, 3</sup>		---	3.5	---	
T <sub>d(off)</sub>	Turn-Off Delay Time <sup>2, 3</sup>		---	14	---	
T <sub>f</sub>	Fall Time <sup>2, 3</sup>		---	6	---	
C <sub>iss</sub>	Input Capacitance	V <sub>DS</sub> =10V , V <sub>GS</sub> =0V , F=1MHz	---	38.2	---	pF
C <sub>oss</sub>	Output Capacitance		---	14.4	---	
C <sub>rss</sub>	Reverse Transfer Capacitance		---	6	---	

### Drain-Source Diode Characteristics and Maximum Ratings


Symbol	Parameter	Conditions	Min.	Typ.	Max.	Unit
I <sub>S</sub>	Continuous Source Current	V <sub>G</sub> =V <sub>D</sub> =0V , Force Current	---	---	750	mA
I <sub>SM</sub>	Pulsed Source Current		---	---	1000	mA
V <sub>SD</sub>	Diode Forward Voltage	V <sub>GS</sub> =0V , I <sub>S</sub> =0.5A , T <sub>J</sub> =25°C	---	---	1.2	V

Note :


1. Repetitive Rating : Pulsed width limited by maximum junction temperature.
2. The data tested by pulsed , pulse width ≤ 300us , duty cycle ≤ 2%.
3. Essentially independent of operating temperature.




**Fig.1 Continuous Drain Current vs.  $T_c$**




**Fig.2 Normalized  $R_{DS(on)}$  vs.  $T_j$**




**Fig.3 Normalized  $V_{th}$  vs.  $T_j$**




**Fig.4 Gate Charge Waveform**




**Fig.5 Normalized Transient Response**




**Fig.6 Maximum Safe Operation Area**




**Fig.7 Switching Time Waveform**



**Fig.8 Gate Charge Waveform**

**Package mechanical data**


Symbol	Millimeters	
	min	max
A	0.4	0.5
A1	0	0.05
D	0.9	1.1
E	0.55	0.65
e	(0.35)	
e1	(0.65)	
b	0.2	0.3
b1	0.2	0.3
L	0.1	0.2
L1	0.45	0.55

**Suggested Land Pattern**


Symbol	Dimension in Millimeters
	typ
X1	(0.3)
X2	(0.35)
Y1	(0.2)
Y2	(0.6)
Z	(0.4)
P	(0.7)

**REEL SPECIFICATION**

P/N	PKG	QTY
MS3134KDFN	DFN1006-3	10000

## Attention

- Any and all MSKSEMI Semiconductor products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your MSKSEMI Semiconductor representative nearest you before using any MSKSEMI Semiconductor products described or contained herein in such applications.
- MSKSEMI Semiconductor assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all MSKSEMI Semiconductor products described or contained herein.
- Specifications of any and all MSKSEMI Semiconductor products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- MSKSEMI Semiconductor strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all MSKSEMI Semiconductor products (including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of MSKSEMI Semiconductor.
- Information (including circuit diagrams and circuit parameters) herein is for example only ; it is not guaranteed for volume production. MSKSEMI Semiconductor believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the MSKSEMI Semiconductor product that you intend to use.