

PRODUCT DATASHEET Brooke-SCR series



| | Ordering number Description | C12083 C12083_Brooke-SCR-M | | |
|-----------|--------------------------------|-------------------------------|-------------|------------|
| | Family | Brooke | FWHM | 23 degrees |
| | Туре | Reflector | Efficiency | - |
| | LED | BXRA-C0400 | cd/lm | - |
| | Color | Metal | Gerber File | Available |
| | Diameter | 45 mm | | |
| | Height | 20.2 mm | | |
| | Style | Round | | |
| | Optic Material | PC | | |
| K. COLOR | Holder Material | - | | |
| | Fastening | Screw, glue | | |
| | Status | Ready | | |
| | Ordering number Description | C12084 C12084_Brooke-SCR-W | | |
| | Family | Brooke | FWHM | 42 degrees |
| | Туре | Reflector | Efficiency | - |
| | LED | BXRA-C0400 | cd/lm | - |
| | Color | Metal | Gerber File | Available |
| | Diameter | 45 mm | | |
| | Height | 20.2 mm | | |
| | Style | Round | | |
| | Optic Material | PC | | |
| ALCO TONS | Holder Material | - | | |
| | Fastening | Screw, glue | | |
| | Status | Ready | | |
| | | nged by different co | | |

ence will be changed by different color, chip size and chip position divergence is the full angle measured where the luminous intensity

Ledil Oy Salorankatu 10 24240 SALO Finland





GENERAL INFORMATION

- Product series especially designed & optimized for BXRA-C0400 series of LEDs.

- Special care taken to make light distribution as uniform as possible.

- Reflector is made of aluminium coated PC (120 degrees of Celcius / 248 degrees of Fahrenheit) with protective lacquer (110 degrees of Celcius / 230 degrees of Fahrenheit).

- Fastening to PCB with appropriate adhesive. By clicking link below you can find Ledil recommended glue options.

http://www.ledil.com/datasheets/DataSheet_GLUES.pdf

NOTE 1: We advise customer to ensure the suitability and sufficiency of the bond in the end product. For example, mechanical stress, vibration and holes on the surface of the circuit boar weaken the strength of the glue.

NOTE 2: All surfaces where glue is applied must be clean, dry and free from grease and dirt. If cleaning of PCB surfaces is needed, please follow strictly the cleaning instructions of your LED manufacturer -this is important as cleaning shall under no circumstances damage LEDs or other electronics components on the PCB.

Further note that optical components shall not be cleaned with any chemicals - only micro fiber cloth may be used to remove fingerprints or other traces from handling.

