

Design Kit

WE-CBF SMD Ferrites Small Size

Order Code 742 790, Version 1.0

Free refill!



Characteristics

- 34 values, 3 types, 1020 components

QR-Code



1

Electrical properties

Order Code	Z @ 100 MHz (Ω)	Z max. (Ω)	R _{DC} (Ω)	I _r (mA)	Qty.	
WE-CBF SMD Ferrites Size 0402						
742 792 701	10	16 @ 1000 MHz	0.05	500	30	
742 792 74	30	43 @ 500 MHz	0.25	300		
742 792 780	220	360 @ 450 MHz	0.40	200		
742 792 71	120	200 @ 600 MHz	0.40	300		
742 792 72	300	400 @ 380 MHz	0.80	200		
742 792 79	600	660 @ 180 MHz	1.00	200		
WE-CBF SMD Ferrites Size 0603						
742 792 68	15	60 @ 1000 MHz	0.10	500		
742 792 67	60	110 @ 650 MHz	0.30	500		
742 792 606	120	575 @ 350 MHz	0.35	200		
742 792 653	600	4500 @ 200 MHz	0.65	300		
742 792 62	120	200 @ 510 MHz	0.30	500		
742 792 63	220	280 @ 350 MHz	0.30	500		
742 792 65	600	720 @ 200 MHz	0.45	200		
742 792 66	1000	1350 @ 140 MHz	0.60	200		
742 792 693	2200	2250 @ 110 MHz	0.80	50		
742 792 604	22	40 @ 1000 MHz	0.05	1000		
742 792 602	60	110 @ 600 MHz	0.04	3000		
742 792 624	180	250 @ 400 MHz	0.09	1500		
742 792 641	300	450 @ 250 MHz	0.15	2000		
742 792 651	600	800 @ 200 MHz	0.20	1000		
WE-CBF SMD Ferrites Size 0805						
742 792 0	11	24 @ 1000 MHz	0.15	600		
742 792 02	120	200 @ 400 MHz	0.10	500		
742 792 042	600	3000 @ 180 MHz	0.50	200		
742 792 038	240	280 @ 250 MHz	0.40	200		
742 792 04	600	700 @ 150 MHz	0.35	200		
742 792 05	1000	1050 @ 120 MHz	0.45	200		
742 792 093	2200	3000 @ 80 MHz	0.60	200		
742 792 011	10	20 @ 1000 MHz	0.025	3000		
742 792 06	30	55 @ 1000 MHz	0.025	3000		
742 792 063	60	90 @ 500 MHz	0.025	3000		
742 792 023	120	180 @ 250 MHz	0.03	3000		
742 792 037	330	375 @ 250 MHz	0.08	2000		
742 792 040	600	700 @ 150 MHz	0.15	2000		
742 792 097	1500	1800 @ 70 MHz	0.30	1000		

Subject to changes