




600E005 MIL-DTL-26500 and MIL-DTL-83723 Series III Plug and Receptacle Holder



RECEPTACLE HOLDER



PLUG HOLDER

Shell Size	Max. Recommended Torque (Inch Pounds)	A Dia. Max.	B Dia. Max.	C Dim. Max.
08	60	.537 (13.6)	.424 (10.8)	1.031 (26.2)
10	80	.660 (16.8)	.526 (13.4)	1.031 (26.2)
12	110	.830 (21.1)	.696 (17.7)	1.031 (26.2)
14	120	.899 (22.8)	.765 (19.4)	1.031 (26.2)
16	120	1.026 (26.1)	.892 (22.7)	1.031 (26.2)
18	120	1.132 (28.8)	.998 (25.3)	1.031 (26.2)
20	140	1.259 (32.0)	1.123 (28.6)	1.031 (26.2)
22	140	1.382 (35.1)	1.248 (31.7)	1.031 (26.2)
24	140	1.509 (38.3)	1.373 (34.9)	1.031 (26.2)
28*	150	1.740 (44.2)	1.623 (41.2)	1.031 (26.2)

* Non-Military standard shell size

APPLICATION NOTES

1. Metric dimensions (mm) are indicated in parentheses.
2. Material: Case hardened carbon steel with electroless nickel finish.
3. Receptacle and plug holder drives: 1/4" - Shell sizes 08, 10, 12; 3/8" - Shell sizes 14 and up.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Glenair:

<u>600E005-18R9</u>	<u>600E005-28P9</u>	<u>600E005-24R6</u>	<u>600E005-20R9</u>	<u>600E005-18PN</u>	<u>600E005-22P8</u>	<u>600E005-22RN</u>
<u>600E005-16P6</u>	<u>600E005-14P6</u>	<u>600E005-12P6</u>	<u>600E005-14R8</u>	<u>600E005-10P7</u>	<u>600E005-16R9</u>	<u>600E005-08PN</u>
<u>600E005-20R6</u>	<u>600E005-18P7</u>	<u>600E005-12R6</u>	<u>600E005-14R6</u>	<u>600E005-18R7</u>	<u>600E005-22P6</u>	<u>600E005-18P6</u>
<u>600E005-24R8</u>	<u>600E005-08P9</u>	<u>600E005-12PN</u>	<u>600E005-08P7</u>	<u>600E005-20P6</u>	<u>600E005-14RN</u>	<u>600E005-24PN</u>
<u>600E005-20PN</u>	<u>600E005-10PN</u>	<u>600E005-08RN</u>	<u>600E005-20RN</u>	<u>600E005-14PN</u>	<u>600E005-14R9</u>	<u>600E005-12R7</u>
<u>600E005-24RN</u>	<u>600E005-24P6</u>	<u>600E005-16RN</u>	<u>600E005-20P7</u>	<u>600E005-28R8</u>	<u>600E005-22PN</u>	<u>600E005-10RN</u>
<u>600E005-28P7</u>	<u>600E005-16PN</u>	<u>600E005-10P6</u>	<u>600E005-12RN</u>	<u>600E005-18R6</u>	<u>600E005-28P6</u>	<u>600E005-28R7</u>
<u>600E005-22P9</u>	<u>600E005-12P7</u>	<u>600E005-16P9</u>	<u>600E005-18RN</u>	<u>600E005-10P8</u>	<u>600E005-20P8</u>	<u>600E005-14P8</u>
<u>600E005-28PN</u>	<u>600E005-28P8</u>	<u>600E005-24P8</u>	<u>600E005-16R6</u>	<u>600E005-12P9</u>	<u>600E005-10R6</u>	<u>600E005-12P8</u>
<u>600E005PN-KIT</u>						